

A1 A - Double-sideband 1 - a single channel containing quantized or digital information without the use of a modulating sub-carrier

A1A	CW	Telegraphy - for aural reception
A1B	CW	Telegraphy - for automatic reception
A1C	FAX	Facsimile
A1D	CW(DSB)	Data transmission, telemetry, telecommand

A2 A- Double-sideband 2- a single channel containing quantized or digital information with the use of a modulating sub-carrier

A2A	CW	Telegraphy - for aural reception
A2B	CW	Telegraphy - for automatic reception
A2C	FAX	Facsimile
A2D		Data transmission, telemetry, telecommand

A3 A- Double-sideband 3- a single channel containing analogue information

A3C	FAX	Facsimile
A3E	AM	Telephony (including sound broadcasting)

F1 F - Frequency modulation, 1 - a single channel containing quantized or digital information without the use of a modulating sub-carrier

F1A	CW	Telegraphy - for aural reception
F1B	RTTY(FSK), SITOR-A, BAUDOT, FSK-Hell	Telegraphy - for automatic reception

F1C FAX Facsimile

F2 F- Frequency modulation, 2 - a single channel containing quantized or digital information with the use of a modulating sub-carrier

F2A	CW	Telegraphy - for aural reception
F2C	FAX	Facsimile
F2D	PACKED(FSK)	Data transmission, telemetry, telecommand

F3 F - Frequency modulation, 3- a single channel containing analogue information

F3C	FAX	Facsimile
F3E	FM	Telephony (including sound broadcasting)
F3F	SSTV	Television (video)
F7W	GMSK	Gaussian Minimum Shift Keyng (D-Star)

G3 G- Phase modulation, 3 - a single channel containing analogue information

G3C	FAX	Facsimile
G3E		Telephony (including sound broadcasting)
G3F		Television (video)

J2 J - Single-sideband, suppressed carrier, 2 - a single channel containing quantized or digital information with the use of a modulating sub-carrier

J2A	CW	Telegraphy - for aural reception
J2B	CW	Telegraphy - for automatic reception
J2C	FAX	Facsimile
J2D	Clover	Data transmission, telemetry, telecommand

J3 J - Single-sideband, suppressed carrier, 3 - a single channel containing analogue information

J3C	FAX	Facsimile
J3E	SSB	Telephony (including sound broadcasting)
J3F	ATV	Television (video)

R3 R - Single-sideband, reduced or variable level carrier, 3 - a single channel containing analogue information

R3C	FAX	Facsimile
R3E	SSB	Telephony (including sound broadcasting)



FM HASIČI

1	169.000	F
2	169.025	G
3	169.050	H
4	169.175	I
5	169.200	J
6	169.225	K
7	169.275	L
8	169.300	M
9	169.325	N
10	169.350	P
11	169.250 MHz	R

JEDNOTKY

YOCTO-	y	10 ⁻²⁴
ZEPTO-	z	10 ⁻²¹
ATTO-	a	10 ⁻¹⁸
FEMTO-	f	10 ⁻¹⁵
PICO-	p	10 ⁻¹²
NANO-	n	10 ⁻⁹
MICRO-	μ	10 ⁻⁶
MILI-	m	10 ⁻³
CENTI-	c	10 ⁻²
DECI-	d	10 ⁻¹
DEKA-	D	10 ¹
HECTO-	h	10 ²
KILO-	k K	10 ³
MEGA-	M	10 ⁶
GIGA-	G	10 ⁹
TERA-	T	10 ¹²
PETA-	P	10 ¹⁵
EXA-	E	10 ¹⁸
ZETTA-	Z	10 ²¹
YOTTA-	Y	10 ²⁴

CTCSS

1.	67.0
-	69.3
2.	71.9
3.	74.4
4.	77.0
5.	79.7
6.	82.5
7.	85.4
8.	88.5
9.	91.5
10.	94.8
11.	97.4
12.	100.0
13.	103.5
14.	107.2
15.	110.9
16.	114.8
17.	118.8
18.	123.0
19.	127.3
20.	131.8
21.	136.5
22.	141.3
23.	146.2
24.	151.4
25.	156.7
-	159.8
26.	162.2
-	165.5
27.	167.9
-	171.3
28.	173.8
-	177.3
29.	179.9
-	183.5
30.	186.2
-	189.9
31.	192.8
32.	203.5
-	206.5
33.	210.7
34.	218.1
35.	225.7
-	229.1
36.	233.6
37.	241.8
38.	250.3
-	254.1

DAB CHANNELS MHz

Band III	L-band
5A 174.928	LA 1452.960
5B 176.640	LB 1454.672
5C 178.352	LC 1456.384
5D 180.064	LD 1458.096
6A 181.936	LE 1459.808
6B 183.648	LF 1461.520
6C 185.360	LG 1463.232
6D 187.072	LH 1464.944
7A 188.928	LI 1466.656
7B 190.640	LJ 1468.368
7C 192.352	LK 1470.080
7D 194.064	LL 1471.792
8A 195.936	LM 1473.504
8B 197.648	LN 1475.216
8C 199.360	LO 1476.928
8D 201.072	LP 1478.640
9A 202.928	LQ 1480.352
9B 204.640	LR 1482.064
9C 206.352	LS 1483.776
9D 208.064	LT 1485.488
10A 209.936	LU 1487.200
10B 211.648	LV 1488.912
10C 213.360	LW 1490.624
10D 215.072	
11A 216.928	
11B 218.640	
11C 220.352	
11D 222.064	
12A 223.936	
12B 225.648	
12C 227.360	
12D 229.072	
13A 230.748	
13B 232.496	
13C 234.208	
13D 235.776	
13E 237.448	
13F 239.200	